

SUPRA QUADRAX COMBICON BI-AMP


High end loudspeaker cable with Banana/Spade

Gauge: 4x2.0mm² / AWG 15


Rev.date: 2022-08-30

Customs tariff no: 8544429010

Country of origin: Sweden



- Star Quad configuration, Bi-Amp
- Tin plated to minimize electron jumps between lead strands
- Interchangeable connectors with M6 thread, banana/spade
- 24K gold plated Copper connectors



QUADRAX COMBICON - Loudspeaker Cable with Emphasis

with Supra CombiCon crimp connectors, Star Quad (4>4) bi-amp version

The tube conductor design means that 120 individually tin plated strands in a braid forms a tube around a PP plastic core. It forces the music signal to meet the same crosssection area irrespective of frequency. The higher frequency, the further out in the conductor perimeter the law of physics forces the signal, hence resulting in unequal conductivity properties for the various frequencies. If adressed in the cable design with tube formed leads we manage the differencies efficiently allowing for a flat frequency response, ultra-fast transients and transparency. If configured in a Star Quad conductor formation (single wire/full range) RFI pickup and outgoing magnetic fields (lowered inductance) are almost completely cancelled out, thanks to the symmetry of current in the opposite conductor pairs. Finally the strand tin plating will counteract any current jumps tendencies between the strands thus creating a diode effect followed by corresponding phase shift.

CombiCon is pressed under high pressure onto the conductor. Done correctly, it brings the material together into an airtight, homogeneous and electrically invisible joint, almost similar to fusion welding.

CONSTRUCTION

Cable: [QUADRAX 4x2.0](#)
 Cross section Area: 4x2.0mm² / AWG 11
 Conductors: + blue/red, - black/white
 Jacket: PVC GA78, round
 Diameter: 15 mm
 Colour: Iceblue (other colours upon order)
 Marking: SUPRA QUADRAX 4x2.0 > Made in Sweden > Meter mark
 Configuration: Stereo pair, 4 > 4 connectors, Right = red, left = black
 Connector: Combicon, 16 x Banana pins & 16 x spades included
 - Material: 24K gold plated Copper
 - Wire connection: Crimp, 16 x CombiCon body CB02 M6
 - Bending protection: Sleeve 8 x S2-4 red, 8 x S2-4 black
 Cable splitt: 20cm, Sleeve 2 x S15 red, 2 x S15 black
 Signal direction: Follow the arrows > amplifier > Speaker
 Packing: Carton 35x35x10 cm



Standard lengths as below, special lengths upon order.

| PRODUCT | Qty | Part.no | EAN-13 | Weight |
|----------------------------------|-------|------------|---------------|--------|
| QUADRAX 4X2.0 BI-AMP COMBICON 2M | 1PAIR | 1000100451 | 7330060203510 | 2,1 |
| QUADRAX 4X2.0 BI-AMP COMBICON 3M | 1PAIR | 1000100469 | 7330060203527 | 2,7 |
| QUADRAX 4X2.0 BI-AMP COMBICON 4M | 1PAIR | 1000100477 | 7330060203534 | 3,2 |